



**Future Technology Devices
International Ltd.**

**AN2232C-01 Command Processor
for MPSSE and MCU Host Bus
Emulation Modes**

1 Command Processor for MPSSE and MCU Host Bus Emulation

1.1 Overview

The FT2232 incorporates a command processor called the Multi-Protocol Synchronous Serial Engine (MPSSE). The purpose of the MPSSE command processor is to communicate with devices which use synchronous protocols (such as JTAG or SPI) in an efficient manner. The FT2232's MCU Host Bus Emulation mode also uses the MPSSE technology to make the chip emulate a standard 8048/8051 MCU host bus.

The MPSSE Command Processor unit is controlled using a SETUP command. Various commands are used to clock data out of and into the chip, as well as controlling the other I/O lines. If disabled the MPSSE is held reset and will not have any effect on the rest of the chip. When enabled, it will take its commands and data from the OUT data written to the OUT pipe in the chip. This is done by simply using the normal WRITE command, as if data were being written to a COM port. Any data read will be passed back in the normal IN pipe. This is done using the normal READ command, as if data were being read from a COM port.

2 Data and Clock Definition

2.1 Data Bit Definition

Data bits are defined according to the following table:

Data Bit	Signal	FT2232 Pin	Type	Description
Bit0	TCK/SK	ADBUS0	Output	Clock Signal Output
Bit1	TDI/DO	ADBUS1	Output	Serial Data Out
Bit2	TDO/DI	ADBUS2	Input	Serial Data In
Bit3	TMS/CS	ADBUS3	Output	Select Signal Out
Bit4	GPIOL0	ADBUS4	Input/Output	General Purpose I/O
Bit5	GPIOL1	ADBUS5	Input/Output	General Purpose I/O
Bit6	GPIOL2	ADBUS6	Input/Output	General Purpose I/O
Bit7	GPIOL3	ADBUS7	Input/Output	General Purpose I/O
Bit8	GPIOH0	ACBUS0	Input/Output	General Purpose I/O
Bit9	GPIOH1	ACBUS1	Input/Output	General Purpose I/O
Bit10	GPIOH2	ACBUS2	Input/Output	General Purpose I/O
Bit11	GPIOH3	ACBUS3	Input/Output	General Purpose I/O

2.2 Clock Operation

The clock will do an XOR of the current state of the TCK/SK pin twice. This means that if the clock pin is set low, then the clock will go high then low to be 1 clock cycle. If the clock pin were set high, then the clock will go low then high to be 1 clock cycle.

3 Command Definitions

3.1 Bad Commands

If the device detects a bad command it will send back 2 bytes to the PC:

0xFA,
followed by the bad command byte.

If the data has got out of sequence then this can be used to determine what that the first pattern was and that an error was detected. The error may have occurred before this (for example sending the wrong amount of data after a write command) and will only trigger when bit 7 of the rogue command is high.

3.2 Data Shifting Command Overview

The data shifting commands are made up of the following definitions :

Data Bit	Definition
Bit 0	-ve TCK/SK on write
Bit 1	bit mode = 1 else byte mode
Bit 2	-ve TCK/SK on read
Bit 3	LSB first = 1 else MSB first
Bit 4	Do write TDI/DO
Bit 5	Do read TDO/DI
Bit 6	Do write TMS/CS
Bit 7	0

The write commands to TDI/DO take effect when bits 7 and 6 are '0'. Read TDO/DI will operate with TMS/CS output or TDI/DO output or on its own.

3.3 MSB First

3.3.1 Clock Data Bytes Out on +ve Clock Edge MSB First (no Read)

Use if TCK/SK starts at '1'.

0x10,
LengthL,
LengthH,
Byte1
..
Byte65536 (max)

This will clock out bytes on TDI/DO from 1 to 65536 depending on the *Length* bytes. A length of 0x0000 will do 1 byte, and a length of 0xFFFF will do 65536 bytes. The data is sent MSB first. Bit 7 of the first byte is placed on TDI/DO then the TCK/SK pin is clocked. The data will change to the next bit on the rising edge of the TCK/SK pin.

3.3.2 Clock Data Bytes Out on -ve Clock Edge MSB First (no read)

Use if TCK/SK starts at '0'.

0x11,
LengthL,
LengthH,
Byte1
..
Byte65536 (max)

This will clock out bytes on TDI/DO from 1 to 65536 depending on the *Length* bytes. A length of 0x0000 will do 1 byte and a length of 0xFFFF will do 65536 bytes. The data is sent MSB first. Bit 7 of the first byte is placed on TDI/DO then the TCK/SK pin is clocked. The data will change to the next bit on the falling edge of the TCK/SK pin.

3.3.3 Clock Data Bits Out on +ve Clock Edge MSB First (no Read)

Use if TCK/SK starts at '1'.

0x12,
Length,
Byte1

This will clock out bits on TDI/DO from 1 to 8 depending on the *Length* byte. A length of 0x00 will do 1 bit and a length of 0x07 will do 8 bits. The data is sent MSB first. Bit 7 of the data byte is placed on TDI/DO then the TCK/SK pin is clocked. The data will change to the next bit on the rising edge of the TCK/SK pin.

3.3.4 Clock Data Bits Out on -ve Clock Edge MSB First (no Read)

Use if TCK/SK starts at '0'.

0x13,
Length,
Byte1

This will clock out bits on TDI/DO from 1 to 8 depending on the *Length* byte. A length of 0x00 will do 1 bit and a length of 0x07 will do 8 bits. The data is sent MSB first. Bit 7 of the data byte is placed on TDI/DO then the TCK/SK pin is clocked. The data will change to the next bit on the falling edge of the TCK/SK pin.

3.3.5 Clock Data Bytes In on +ve Clock Edge MSB First (no Write)

0x20,
LengthL,
LengthH

This will clock in bytes on TDO/DI from 1 to 65536 depending on the *Length* bytes. A length of 0x0000 will do 1 byte and a length of 0xFFFF will do 65536 bytes. The first bit clocked in will be the MSB of the first byte and so on. The data will be sampled on the rising edge of the TCK/SK pin.

3.3.6 Clock Data Bytes In on -ve Clock Edge MSB First (no Write)

0x24,
LengthL,
LengthH

This will clock in bytes on TDO/DI from 1 to 65536 depending on the *Length* bytes. A length of 0x0000 will do 1 byte and a length of 0xFFFF will do 65536 bytes. The first bit clocked in will be the MSB of the first byte and so on. The data will be sampled on the falling edge of the TCK/SK pin.

3.3.7 Clock Data Bits In on +ve Clock Edge MSB First (no Write)

TDO/DI sampled just prior to rising edge

0x22,
Length

This will clock in bits on TDO/DI from 1 to 8 depending on the *Length* byte. A length of 0x00 will do 1 bit and a length of 0x07 will do 8 bits. The data will be shifted up so that the first bit in may not be in bit 7, but from 6 downwards depending on the number of bits to shift (i.e. a length of 1 bit will have the data bit sampled in bit 0 of the byte sent back to the PC). The data will be sampled on the rising edge of the TCK/SK pin.

3.3.8 Clock Data Bits In on -ve Clock Edge MSB First (no Write)

TDO/DI sampled just prior to falling edge

0x26,
Length

This will clock in bits on TDO/DI from 1 to 8 depending on the *Length* byte. A length of 0x00 will do 1 bit, and a length of 0x07 will do 8 bits. The data will be shifted up so that the first bit in may not be in bit 7, but from 6 downwards depending on the number of bits to shift (i.e. a length of 1 bit will have the data bit sampled in bit 0 of the byte sent back to the PC). The data will be sampled on the falling edge of the TCK/SK pin.

3.3.9 Clock Data Bytes In and Out MSB First

Out on positive edge, in on positive edge

0x30,
LengthL,
LengthH,
Byte1,
..
Byte65536 (max)

or

Out on negative edge, in on positive edge

0x31,
LengthL,
LengthH,
Byte1
..
Byte65536 (max)

or

Out on positive edge, in on negative edge

0x34,
LengthL,
LengthH,
Byte1
..
Byte65536 (max)

or

Out on negative edge, in on negative edge

0x35,
LengthL,
LengthH,
Byte1
..
Byte65536 (max)

3.3.10 Clock Data Bits In and Out MSB First

Out on positive edge, in on positive edge

*0x32,
Length,
Byte*

or

Out on negative edge, in on positive edge

*0x33,
Length,
Byte*

or

Out on positive edge, in on negative edge

*0x36,
Length,
Byte*

or

Out on negative edge, in on negative edge

*0x37,
Length,
Byte*

3.4 LSB First

3.4.1 Clock Data Bytes Out on +ve Clock Edge LSB First (no Read)

Use if TCK/SK starts at '1'

0x18,
LengthL,
LengthH,
Byte1,
..
Byte65536 (max)

This will clock out bytes on TDI/DO from 1 to 65536 depending on the *Length* bytes. A length of 0x0000 will do 1 byte and a length of 0xFFFF will do 65536 bytes. The data is sent LSB first. Bit 0 of the first byte is placed on TDI/DO then the TCK/SK pin is clocked. The data will change to the next bit on the rising edge of the TCK/SK pin.

3.4.2 Clock Data Bytes Out on -ve Clock Edge LSB First (no Read)

Use if TCK/SK starts at '0'.

0x19,
LengthL,
LengthH,
Byte1,
..
Byte65536 (max)

This will clock out bytes on TDI/DO from 1 to 65536 depending on the *Length* bytes. A length of 0x0000 will do 1 byte and a length of 0xFFFF will do 65536 bytes. The data is sent LSB first. Bit 0 of the first byte is placed on TDI/DO then the TCK/SK pin is clocked. The data will change to the next bit on the falling edge of the TCK/SK pin.

3.4.3 Clock Data Bits Out on +ve Clock Edge LSB First (no Read)

Use if TCK/SK starts at '1'.

0x1A,
Length,
Byte1

This will clock out bits on TDI/DO from 1 to 8 depending on the *Length* byte. A length of 0x00 will do 1 bit and a length of 0x07 will do 8 bits. The data is sent LSB first. Bit 0 of the data byte is placed on TDI/DO then the TCK/SK pin is clocked. The data will change to the next bit on the rising edge of the TCK/SK pin.

3.4.4 Clock Data Bits Out on -ve Clock Edge LSB First (no Read)

Use if TCK/SK starts at '0'.

0x1B,
Length,
Byte1

This will clock out bits on TDI/DO from 1 to 8 depending on the *Length* byte. A length of 0x00 will do 1 bit and a length of 0x07 will do 8 bits. The data is sent LSB first. Bit 0 of the data byte is placed on TDI/DO then the TCK/SK pin is clocked. The data will change to the next bit on the falling edge of the TCK/SK pin.

3.4.5 Clock Data Bytes In on +ve Clock Edge LSB First (no Write)

0x28,
LengthL,
LengthH

This will clock in bytes on TDO/DI from 1 to 65536 depending on the *Length* bytes. A length of 0x0000 will do 1 byte and a length of 0xFFFF will do 65536 bytes. The first bit clocked in will be the LSB of the first byte and so on. The data will be sampled on the rising edge of the TCK/SK pin.

3.4.6 Clock Data Bytes In on -ve Clock Edge LSB First (no Write)

0x2C,
LengthL,
LengthH

This will clock in bytes on TDO/DI from 1 to 65536 depending on the *Length* bytes. A length of 0x0000 will do 1 byte and a length of 0xFFFF will do 65536 bytes. The first bit clocked in will be the LSB of the first byte and so on. The data will be sampled on the falling edge of the TCK/SK pin.

3.4.7 Clock Data Bits In on +ve Clock Edge LSB First (no Write)

TDO/DI sampled just prior to rising edge

0x2A,
Length

This will clock in bits on TDO/DI from 1 to 8 depending on the *Length* byte. A length of 0x00 will do 1 bit and a length of 0x07 will do 8 bits. The data will be shifted down so that the first bit in may not be in bit 0, but from 1 upwards depending on the number of bits to shift (i.e. a length of 1 bit will have the data bit sampled in bit 7 of the byte sent back to the PC). The data will be sampled on the rising edge of the TCK/SK pin.

3.4.8 Clock Data Bits In on -ve Clock Edge LSB First (no Write)

TDO/DI sampled just prior to falling edge

0x2E,
Length

This will clock in bits on TDO/DI from 1 to 8 depending on the *Length* byte. A length of 0x00 will do 1 bit and a length of 0x07 will do 8 bits. The data will be shifted down so that the first bit in may not be in bit 0, but from 1 upwards depending on the number of bits to shift (i.e. a length of 1 bit will have the data bit sampled in bit 7 of the byte sent back to the PC). The data will be sampled on the falling edge of the TCK/SK pin.

3.4.9 Clock Data Bytes In and Out LSB First

Out on positive edge, in on positive edge

0x38,
LengthL,
LengthH,
Byte1,
..
Byte65536 (max)

or

Out on negative edge, in on positive edge

0x39,
LengthL,
LengthH,
Byte1,
..
Byte65536 (max)

or

Out on positive edge, in on negative edge

0x3C,
LengthL,
LengthH,
Byte1,
..
Byte65536 (max)

or

Out on negative edge, in on negative edge

0x3D,
LengthL,
LengthH,
Byte1,
..
Byte65536 (max)

3.4.10 Clock Data Bits In and Out LSB First

Out on positive edge, in on positive edge

*0x3A,
Length,
Byte*

or

Out on negative edge, in on positive edge

*0x3B,
Length,
Byte*

or

Out on positive edge, in on negative edge

*0x3E,
Length,
Byte*

or

Out on negative edge, in on negative edge

*0x3F,
Length,
Byte*

3.5 TMS Commands

3.5.1 Clock Data to TMS/CS Pin (no Read)

*0x4A or 0x4B,
Length,
Byte1*

This will send data bits 6 down to 0 to the TMS/CS pin using the LSB or MSB and -ve or +ve TCK/SK, depending on which of the lower bits have been set.

0x4A : TMS/CS with LSB first on +ve TCK/SK edge - use if TCK/SK is set to '1'
0x4B : TMS/CS with LSB first on -ve TCK/SK edge - use if TCK/SK is set to '0'

Bit 7 of the Byte1 is passed on to TDI/DO before the first TCK/SK of TMS/CS and is held static for the duration of TMS/CS clocking. No read operation will take place.

3.5.2 Clock Data to TMS/CS Pin with Read

0x6A or 0x6B or 0x6E or 0x6F

Length,

Byte1

This will send data bits 6 down to 0 to the TMS/CS pin using the LSB or MSB and -ve or +ve TCK/SK, depending on which of the lower bits have been set.

0x6A : TMS/CS with LSB first on +ve TCK/SK edge, read on +ve edge - use if TCK/SK is set to '1'

0x6B : TMS/CS with LSB first on -ve TCK/SK edge, read on +ve edge - use if TCK/SK is set to '0'

0x6E : TMS/CS with LSB first on +ve TCK/SK edge, read on -ve edge - use if TCK/SK is set to '1'

0x6F : TMS/CS with LSB first on -ve TCK/SK edge, read on -ve edge - use if TCK/SK is set to '0'

Bit 7 of the Byte1 is passed on to TDI/DO before the first TCK/SK of TMS/CS and is held static for the duration of TMS/CS clocking. The TDO/DI pin is sampled for the duration of TMS/CS and a byte containing the data is passed back at the end of TMS/CS clocking.

3.6 Set / Read Data Bits High / Low Bytes

3.6.1 Set Data Bits Low Byte

0x80,
0xValue,
0xDirection

This will setup the direction of the first 8 lines and force a value on the bits that are set as output. A '1' in the *Direction* byte will make that bit an output.

3.6.2 Set Data Bits High Byte

0x82,
0xValue,
0xDirection

This will setup the direction of the high 4 lines and force a value on the bits that are set as output. A '1' in the *Direction* byte will make that bit an output.

3.6.3 Read Data Bits Low Byte

0x81

This will read the current state of the first 8 pins and send back 1 byte.

3.6.4 Read Data Bits High Byte

0x83

This will read the current state of the high 4 pins and send back 1 byte.

3.7 Loopback Commands

3.7.1 Connect TDI/DO to TDO/DI for Loopback

0x84

This will connect the TDI/DO output to the TDO/DI input for loopback testing.

3.7.2 Disconnect TDI/DO to TDO/DI for Loopback

0x85

This will disconnect the TDI/DO output from the TDO/DI input for loopback testing.

3.8 Clock Divisor

3.8.1 Set TCK/SK Divisor

0x86,
0xValueL,
0xValueH

This will set the clock divisor.

The TCK/SK always has a duty cycle of 50%, except between commands where it will remain in its initial state. The initial state is set using the 23. Set Data Bits Low Byte command. For example, to use it in JTAG mode you would issue:-

```
$80 Set Data Bits Low Byte
$08 TCK/SK, TDI/DU low, TMS/CS high
$0B TCK/SK, TDI/DU, TMS/CS output, TDO/D1 and GPIOL1 -> 14 input
```

The clock will then start low. When the MPSSE is sent a command to clock bits (or bytes) it will make the clock go high and then back low again as 1 clock period. For TMS/CS commands, a \$4B command would be used for no read, and a \$6B command for TMS/CS with read. For clocking data out on TDI/DU with no read of TDO/D1, a \$19 command would be used for bytes and \$1B for bits. To read from TDO/D1 with no data sent on TDI/DU a \$28 command would be used for bytes and \$2A for bits. To scan in and out at the same time a \$39 command would be used for bytes and \$3B for bits.

The TCK/SK frequency can be worked out using the following algorithm :

$$\text{TCK/SK period} = 12\text{MHz} / ((1 +[(0xValueH * 256) \text{ OR } 0xValueL]) * 2)$$

For example:

Value	TCK/SK Max
0x0000	6 MHz
0x0001	3 MHz
0x0002	2 MHz
0x0003	1.5 MHz
0x0004	1.2 MHz
.....
0xFFFF	91.553 Hz

4 Instructions for MCU Host Bus Emulation Mode

4.1 Overview

MCU Host Bus Emulation mode makes the chip emulate a CPU with:

- a) a multiplexed 8 bit address and data bus
- b) an extended 8 bit address bus
- c) CS# , ALE, WR# , RD# and OSC signals
- d) 2 I/O lines that can be used as extra I/O or to wait for IRQs. These are defined as I/O0 and I/O1.

4.2 MCU Host Emulation Mode Read Short Address

0x90,
0xAddrLow

This will read 1 byte.

4.3 MCU Host Emulation Mode Read Extended Address

*0x91,
0xAddrHigh,
0xAddrLow*

This will read 1 byte.

4.4 MCU Host Emulation Mode Write Short Address

0x92,
0xAddrLow,
0xData

This will write 1 byte.

4.5 MCU Host Emulation Mode Write Extended Address

0x93,
0xAddrHigh,
0xAddrLow,
0xData

This will write 1 byte.

5 Instructions for use in both MPSSE and MCU Host Emulation Modes

5.1 Send Immediate

0x87

This will make the chip flush its buffer back to the PC.

5.2 Wait On I/O High

0x88

This will cause the controller to wait until GPIOH1 (MPSSE) or I/O1 (MCU Host Bus Emulation) is high. Once it is detected as high, it will move on to process the next instruction. The only way out of this will be to disable the controller if the I/O line never goes high.

5.3 Wait On I/O Low

0x89

This will cause the controller to wait until GPIOH1 (MPSSE) or I/O1 (MCU Host Emulation) is low. Once the pin is detected as low, it will move on to process the next instruction. The only way out of this will be to disable the controller if the I/O line never goes low.

6 History, Disclaimer, Contact Information

6.1 Document Revision History

Version	Release Date	Comments
1.0	March 2004	Initial release.
1.1	April 2004	Overview rewritten. Signal names made consistent. FT2232C pin and signal names added to data bit definition table. MSB and LSB command names updated. Set TCK/SK Divisor expanded. Further examples added. Command 2. Clock Data Bytes Out on -ve Clock Edge MSB First (no Read) was missing
2.0	December 2005	Minor corrections. New format.
2.1	March 2006	Data bit definition signals corrected.
2.2	October 2006	References to FT2232C changed to FT2232 after release of FT2232D.

6.2 Disclaimer

Copyright © 2006 Future Technology Devices International Ltd.

Neither the whole nor any part of the information contained in, or the product described in this manual, may be adapted or reproduced in any material or electronic form without the prior written consent of the copyright holder.

This product and its documentation are supplied on an as-is basis and no warranty as to their suitability for any particular purpose is either made or implied. Future Technology Devices International Ltd. will not accept any claim for damages howsoever arising as a result of use or failure of this product. Your statutory rights are not affected.

This product or any variant of it is not intended for use in any medical appliance, device or system in which the failure of the product might reasonably be expected to result in personal injury.

This document provides preliminary information that may be subject to change without notice.

6.3 Contact Information

Head Office - Glasgow, UK

Future Technology Devices International Limited
373 Scotland Street
Glasgow
G5 8QB
United Kingdom
Tel: +44 (0) 141 429 2777
Fax: +44 (0) 141 429 2758

E-Mail (Sales): sales1@ftdichip.com
E-Mail (Support): support2@ftdichip.com
E-Mail (General Enquiries): admin1@ftdichip.com
Web Site URL: <http://www.ftdichip.com>
Web Shop URL: <http://apple.clickandbuild.com/cnb/shop/ftdichip>

Branch Office - Taiwan

Future Technology Devices International Limited (Taiwan)
4F, No 16-1, Sec. 6 Mincyuan East Road
Neihu District
Taipei 114
Taiwan
ROC
Tel: +886 2 8791 3570
Fax: +886 2 8791 3576

E-Mail (Sales): tw.sales1@ftdichip.com
E-Mail (Support): tw.support1@ftdichip.com
E-Mail (General Enquiries): tw.admin1@ftdichip.com
Web Site URL: <http://www.ftdichip.com>

Branch Office - Hillsboro, Oregon, USA

Future Technology Devices International Limited (USA)
5285 NE Elam Young Parkway
Suite B800
Hillsboro, OR 97124-6499
USA
Tel: +1 (503) 547-0988
Fax: +1 (503) 547-0987

E-Mail (Sales): us.sales@ftdichip.com
E-Mail (Support): support2@ftdichip.com
E-Mail (General Enquiries): admin1@ftdichip.com
Web Site URL: <http://www.ftdichip.com>

Agents and Sales Representatives

Please visit the [Sales Network](#) page of the [FTDI Web site](#) for the contact details of our distributor(s) in your country.

Index

- 0 -

0x10	7
0x11	8
0x12	9
0x13	10
0x18	17
0x19	18
0x1A	19
0x1B	20
0x20	11
0x22	13
0x24	12
0x26	14
0x28	21
0x2A	23
0x2C	22
0x2E	24
0x30	15
0x31	15
0x32	16
0x33	16
0x34	15
0x35	15
0x36	16
0x37	16
0x38	25
0x39	25
0x3A	26
0x3B	26
0x3C	25
0x3D	25
0x3E	26
0x3F	26
0x4A	27
0x4B	27
0x6A	28
0x6B	28
0x6E	28
0x6F	28
0x80	29

0x81	31
0x82	30
0x83	32
0x84	33
0x85	34
0x86	35
0x87	41
0x88	42
0x89	43
0x90	37
0x91	38
0x92	39
0x93	40
0xFA	5

- A -

ALE	36
-----	----

- B -

Bad Commands	5
bit mode	6

- C -

CLK	3, 4, 6
CLK Divisor	35
Clock	4
Clock Divisor	35
Command Processor	2
Contact	46
CS#	36

- D -

D0	3
Data Bits	3
Data Shifting commands	6
DI	3
Disclaimer	45
Document Revision History	44
Duty Cycle	35

- E -

E-mail 46

- F -

FT2232 2

- G -

GPIO11 3

GPIO12 3

GPIO13 3

GPIO14 3

GPIO21 3

GPIO22 3

GPIO23 3

GPIO24 3

- I -

IRQ 36

- J -

JTAG 2

- L -

LSB 6, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 28

- M -

MCU Host Bus Emulation 2, 36, 41, 42, 43

MPSSE 2, 41, 42, 43

MSB 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 28

Multi-Protocol Synchronous Serial Engine 2

- O -

OSC 36

- R -

RD# 36

- S -

Send Immediate 41

SETUP Command 2

SPI Bus 2

- T -

TCLK 35

TDI 6, 27, 33, 34

TDO 6, 28, 33, 34

TMS 3, 6, 27, 28

- W -

WR# 36

- X -

XOR 4